

## RC5000 Series

带有安装脚的铁氧体磁芯(ferrite core)



### 用途

信号线、开关电源以及变频器电源等

### 规格

| Measurement temperature 23+/-2Deg.C |            |            |               |     |     |     |    |          |          |         |
|-------------------------------------|------------|------------|---------------|-----|-----|-----|----|----------|----------|---------|
| Type                                | 100KHz(uH) | 500KHz(uH) | Dimension(mm) |     |     |     |    |          |          |         |
|                                     |            |            | A             | B   | C   | D   | E  | F        | G        | H       |
| RC5047                              | 6.86-10.94 | >=3.11     | 54            | 49  | 75  | 90  | 16 | dia.5    | R2.5 L10 | dia.25  |
| RC5060                              | 6.02-9.60  | >=1.50     | 67            | 62  | 95  | 115 | 19 | dia.5    | R2.5 L10 | dia.38  |
| RC5078                              | 7.53-11.30 | >=1.30     | 85            | 80  | 130 | 150 | 23 | dia.7    | R3.5 L14 | dia.48  |
| RC5096                              | 4.71-7.07  | >=1.30     | 103           | 98  | 140 | 160 | 25 | dia.7    | R3.5 L14 | dia.72  |
| RC5128                              | >=5.20     | >=1.30     | 138           | 130 | 160 | 180 | 34 | dia.7    | R3.5 L14 | dia.99  |
| RC5200                              | >=7.70     | -          | 220           | -   | 220 | 241 | 48 | R3.5 L15 | R3.5 L15 | dia.148 |

Note: Measured by YHP manufactured multi-frequency LCR meter 4284A the equivalent meter.  
Condition for the measurement f=100KHz,500KHz 1T 10mA through.

### 形状图



